

# RF13.2 - Handset with control

Type designation: **RF13.2**

NSN: **5965160034636**

PN (RN): **2022.100.01**

KČN: **0064333000661**

The handset can be connected to any of the two audio connectors on the RF13 transceiver or to any transceiver accessory featuring an audio connector. Along with handset functions, it also features transceiver remote control and function mode display. The construction guarantees mechanical resistance, watertightness and stiffness.

## Technical parameters

**Power supply from the RF13 transceiver or from accessory.**

**Control functions**

- **two step volume control, channel selection, start and stop of scanning**
- **clear override**
- **selection of displayed information type - channel/frequency**
- **handset display illumination**
- **PTT switch**
- **audio tone signalling**

**Handset display information**

- **selective communication**
- **in the reception and transmission mode displays a symbolic channel number or the frequency**
- **scanning**
- **clear override**

- in short coded messages mode, it displays a two-digit code of the transmitting station's address and the signal code

- voice encryption mode

<b>Microphone</b>	piezoceramic
<b>Microphone sensitivity</b>	100 mV (1 kHz/20 mm/80 dB)
<b>Earphone</b>	electrodynamic loudspeaker
<b>Earphone sensitivity</b>	min. 90 dB (900 mV/1 kHz/20 mm)
<b>Impedance</b>	30 Ω
<b>After pressing the LITE pushbutton the display will be illuminated for</b>	(10 ± 3) s
<b>Operating temperature range</b>	-30 °C to +60 °C
<b>Weight</b>	0.4 kg

## Documentation

<b>RF13.2 operating instructions</b>	2022.010.02
--------------------------------------	-------------

## Set

<b>Type designation</b>	<b>PN (RN)</b>	<b>Name</b>
RF13.2	2022.000.01	Handset with control set