

GTR52 - Time and frequency transfer GNSS receiver

Type designation: **GTR52**

PN (RN): **2065.100.20, 2065.100.21, 2065.100.22**

The GTR52 is a multisystem/multifrequency GNSS (Global Navigation Satellite System) receiver intended for time and frequency transfer. The receiver supports both code and phase measurements using signals of several systems in several frequency channels. Thanks to large receiver bandwidth and advanced signal processing, even the code measurements provide sub-nanosecond accuracy. Critical elements are placed in a thermostat box. The receiver can be directly connected to a local net/internet which allows remote control and output data download and upload.

Unlike GTR51, the GTR52 receiver doesn't support GLONASS system and doesn't have internal time reference output.

The receiver is produced in three variants, see table.

DEVICE		SYSTEMS		
		GPS	GALILEO	SBAS
GTR52	2065.100.20	•	•	•
	2065.100.21	•		•
	2065.100.22	•		

Description

Operation

The operation is fully automatic. After the very first configuration, the receiver continuously collects the measurement data. Output files in several standard/proprietary formats can be generated from the collected data. The data processing can be started manually or by a scheduler which enables routine processing at given times (daily, weekly, ...). The resulting data files can be downloaded from the receiver, automatically uploaded to a server or automatically saved to an external disk. A brief message is sent to an e-mail address after the processing is finished.

The output measurement data are referenced to the input 1PPS time mark.

Remote control

The receiver can be controlled from any computer on the net. The User Interface has the form of a web page which can be accessed using a web browser. It enables control of the receiver, monitoring of the receiver operation, and download of the measurement data. Authorization is required to access the receiver.

Diagnostic system

The diagnostic system indicates several dozens of operational events and states. The diagnostic messages can be recorded in the log, displayed in the User Interface, and sent to an e-mail address.

Monitoring with graphical representation

History of operational parameters (time difference, temperature, satellite elevation/azimuth, ...) is displayed in graphs in the User Interface.

Technical parameters

TIME REFERENCE INPUT

Input signal	1PPS (leading edge)
Input impedance	50 Ω
Trigger level	0 V-2 V adjustable
Max level	5.5 V/50 Ω
Min level	-0.1 V/50 Ω

The 1PPS mark must be coherent with the frequency reference at the 10 MHz input.

FREQUENCY REFERENCE INPUT

Input signal	10 MHz
Input impedance	50 Ω
Max level	3 Vpp/50 Ω
Min level	0.5 Vpp/50 Ω

PRECISION

Code measurement	< 0.5 ns rms (CGGTTS data, short-baseline common view, GPS, GALILEO)
-------------------------	--

Phase measurement	< 30 ps rms (short-baseline common view)
OUTPUT DATA FORMATS	
CGGTTS	all tracks/all satellites in view, MSIO iono-delay, versions 01 and 02
RINEX	observation/navigation files, versions 2.10 (GPS only), 2.11 and 3.01
RAW	proprietary format, all signals, both code and carrier phase data
EL_MASK	CNR analysis and search for obstacles
STAT	statistics of collected measurement data
L3P_30s	standard P3 data, 30 s sampling period
L3P_1s	P3 data, 1 s sampling period
BETA	proprietary format similar to planned CGGTTS V03, GPS, GALILEO
1PPS_DIF	proprietary format, 1PPS_IN - 1PPS_INT difference
GNSS RECEIVER	
Supported signals	
GPS: L1C/A , L1P, L2C, L2P, L5	
GALILEO: E1, E5a	
SBAS: L1, L5	
Type of measurement	code/carrier phase referenced to input 1PPS
Receiver bandwidth	24 MHz
Number of satellites	all in view
TIME INTERVAL COUNTER	
Precision	< 15 ps rms
Thermostat	based on thermoelectric modules
Dimensions	19"/2U standard chassis
Power supply	100 V-240 V AC/50 Hz-60 Hz
Operating temperature	0 °C to 50 °C

ANTENNA

Antenna supply

5 V/up to 90 mA (plus on inner contact)

Recommended antenna

Novatel GPS-702-GGG (2065.525.03), Novatel GPS-703-GGG (2065.525.10)

Documentation

GTR51, GTR52 operating instructions

2065.010.12

Set

Type designation	PN (RN)	Name
GTR52	2065.000.20	Time and frequency transfer GNSS receiver set
GTR52	2065.000.21	Time and frequency transfer GNSS receiver set
GTR52	2065.000.22	Time and frequency transfer GNSS receiver set