

# NK13 - Trickle charger

Type designation: **NK13**

NSN: **6130160037999**

PN (RN): **7002.100.02**

KČN: **0299012010862**

The charger is used for elimination of self-discharging of NiCd battery packs RF13.1 during storage. Charged battery packs are stored close to the trickle charger. They are interconnected with a cable (7002.900.01). One trickle charger can charge up to 30 battery packs at the same time.

## Technické parametry

<b>Napájecí napětí</b>	síťové 230 V/50 Hz
<b>Doba nabíjení</b>	neomezena
<b>Nabíjecí proud</b>	30 mA
<b>Řízení nabíjení</b>	konstantní nabíjecí proud
<b>Krytí</b>	IP 30
<b>Rozsah pracovních teplot</b>	-20 °C až +50 °C
<b>Rozměry [š x v x h]</b>	340 mm x 95 mm x 255 mm
<b>Hmotnost</b>	4 kg

## Průvodní dokumentace

<b>Návod k obsluze NK13</b>	7002.010.01
<b>Záznamník</b>	6000002011
<b>Technický list</b>	6000002021

## Set

Type designation	PN (RN)	Name
NK13	7002.000.02	Trickle charger set

# Batteries

Type designation	PN (RN)	Name
RF13.1	7000.000.02	Rechargeable battery pack set