

# RN13.1 - Quick battery charger

Type designation: **RN13.1**

NSN: **6130160041837**

PN (RN): **7001.100.11**

KČN: **0068600200055**

The quick charger is used for quick charging of one or two battery packs RF13.1. Simultaneously, it can control and test other battery packs. Charged battery packs are fastened to the charger by means of level closures. The charger can be carried with the charged batteries.

## Technické parametry

<b>Napájecí napětí</b>	síťové 230 V/50 Hz
<b>Doba nabíjení</b>	60 minut
<b>Nabíjecí proud</b>	0,2 A až 6 A, řízeno procesorem podle nabíjecí charakteristiky
<b>Řízení nabíjení</b>	podle poklesu napětí, teploty baterie max. 45 °C a času 60 minut
<b>Kontrola zdrojové skříně</b>	měření napětí skříně naprázdno / měření napětí při zatěži 4 A po stisknutí tlačítka TEST
<b>Rozsah voltmetru</b>	0 V až 15 V
<b>Krytí</b>	IP 30
<b>Rozsah prac. teplot</b>	-20 °C až +50 °C
<b>Rozměry [š x v x h]</b>	
<b>Hmotnost</b>	10,5 kg

# Průvodní dokumentace

<b>Návod k obsluze RN13.1</b>	7001.010.11
<b>Záznamník</b>	6000002011
<b>Technický list</b>	6000002021

## Set

<b>Type designation</b>	<b>PN (RN)</b>	<b>Name</b>
RN13.1	7001.000.11	Quick battery charger set

## Battery packs

<b>Type designation</b>	<b>PN (RN)</b>	<b>Name</b>
RF13.1	7000.000.01	Rechargeable battery pack set