

# NS13 - Standard battery charger

Type designation: **NS13**

NSN: **6130160037710**

PN (RN): **7003.100.01**

KČN: **0299012010800**

The charger is used for simultaneous charging of one to six rechargeable battery packs RF13.1 at 0.1 C standard current. Temperature increase of the battery pack above +43 °C causes the standard charging current switch-off and consequently the trickle charge mode is switched on. Charged battery packs are fastened to the charger by means of level closures. The charger can be carried with the charged battery packs.

## Technické parametry

<b>Napájecí napětí</b>	síťové 230 V/50 Hz
<b>Doba nabíjení</b>	(14 až 16) hodin
<b>Nabíjecí proud</b>	400 mA
<b>Konzervační proud</b>	30 mA
<b>Krytí</b>	IP 30
<b>Rozsah prac. teplot</b>	-20 °C až +50 °C
<b>Rozměry [š x v x h]</b>	225 mm x 250 mm x 315 mm
<b>Hmotnost</b>	5,5 kg

## Průvodní dokumentace

<b>Návod k obsluze NS13</b>	7003.010.01
<b>Zánamník</b>	6000002011
<b>Technický list</b>	6000002021

## Set

Type designation	PN (RN)	Name
NS13	7003.000.01	Standard battery charger set

## Battery packs

Type designation	PN (RN)	Name
RF13.1	7000.000.01	Rechargeable battery pack set